

LEDEMERGENCYINVERTER (FORINTERNALDRIVER)



Features:

- Durable heavy duty steel housing
- Innovative, easy installation in minutes
- 120-277VAC Universal voltage operation
- Built-in Nickel cadmium battery for minimum 90 minutes emergency operation.
- Working voltage 180VDC(OR 120VAC)
- Suitable with LED fixtures up to 20W(for internal driver only) and provide 100% lumen output.
- Maximum 24 hours for full recharge time
- Test switch and charge indicator
- UL and cULus listed
- 0° to 40°C indoor damp location listed
- Three years warranty.

